

## TC400D Jumper Position for 2.x PROM's

To use the TC400D version 2.x software it is necessary to change the position of jumper J8 to accommodate the new, larger capacity PROM's.

If the CPU board has a movable jumper at J8, move it from ~~256~~ position to the ~~512~~ position.

If the CPU board has a soldered-in jumper:

1. Clip out the wire soldered in the ~~256~~ position of J8.
2. Solder a jumper in the ~~512~~ position of J8, as shown on the layout drawing.

Note: Do not change the J9 jumper position.

