

# BrightEye 33

## Amplificador de Distribución de Audio Analógico

BrightEye 33 es un amplificador de distribución de audio de alta performance para broadcast y la industria de grabación. Las excepcionales características de performance incluyen excelentes especificaciones de respuesta, ruido, y distorsión. BrightEye 33 funciona tanto con 8 salidas mono o con 4 salidas estereo.

Los ajustes de ganancia son accesibles desde el panel frontal. Este es un dispositivo simple sin port USB ni interface con los softwares BrightEye Mac o PC.



- ▶ DA de audio analógico para broadcast y post
- ▶ 8 salidas mono o 4 salidas estereo
- ▶ Ajustes de ganancia desde el panel frontal

## ► Specifications

### Analog Audio Inputs

Number	Two
Type	Balanced
Impedance	>15K
Maximum Input Level	24 dBu
CMRR	>60 dB, 20 Hz to 10 KHz

### Analog Audio Outputs

Number	Four stereo or eight mono
Type	Balanced, transformerless
Impedance	30
Maximum Output Level	24 dBu

### Performance

Gain Range	$\pm 6$ dB
Frequency Response	$< \pm 0.1$ dB, 20 Hz to 20 KHz
Isolation	>100 dB
S/N Ratio	>100 dB, unweighted

### General Specifications

Size	5.625" W x 0.8" H x 5.5" D (143 mm x 20 mm x 140 mm) including connectors
Power	12 volts, 4 watts (100-230 VAC modular power supply not included)
Temperature Range	0 to 40° C ambient
Relative Humidity	0 to 95% non-condensing
Altitude	0 to 10,000 ft.